



Caiman Quick Connect

Wire a side mains cable entry without needing to open luminaire (product is through-wired)

Features		Installation Information	
IP rating	IP66	Input	220-240V AC
IK rating	IK10	Maximum Ambient Temperature	-20°C - 35°C
CSP Switchable	Switchable CCT	Weight	1.3 - 2.15kg
Sensor Option	MW On-Off	Inrush Current	16A 0.51ms
Dimmable Option	No	Construction Material	Polycarbonate Housing (RAL7005), Anti-UV Diffuser
LED Lifetime	L70 100,000h	SELV	No
Colour Rendering Index	CRI>80	Electric Class (1, 2, 3)	1
Colour Consistency	SDCM6	Install Connector Type	Removeable, moveable, loop in/out
Emergency Option	No	UK Building Regulations	Part L
		Power Factor	0.9

Photometrics @ 25°C

Product Code	Type	Beam	W	Colour	lm	lm/W	EM lm	Energy
AC4TWN	Standard	120°	18W	3000K	2590	144	N/A	
				4000K	2775	154	N/A	
				5700K	2775	154	N/A	
			37W	3000K	5180	144	N/A	
				4000K	5550	154	N/A	
AC5TWN	Standard	120°	28W	5700K	5550	154	N/A	
				3000K	3920	140	N/A	
				4000K	4200	150	N/A	
			56W	5700K	4200	150	N/A	
				3000K	7840	140	N/A	
AC6TWN	Standard	120°	33W	4000K	8400	150	N/A	
				5700K	8400	150	N/A	
				3000K	4690	142	N/A	
			67W	4000K	5025	152	N/A	
				5700K	5025	152	N/A	
				3000K	9380	140	N/A	
				4000K	10050	150	N/A	
				5700K	10050	150	N/A	

Energy rating is a reflection of the LED light source.

Wiring Information

Cable Required for Connector	N/A
Type of Wiring Required	Parallel

Accessories

ACKITMWS	Microwave Sensor on/off Plug-in Kit (Assembled on demand by Collingwood Production)	Sold Separately
----------	---	-----------------



CCT switchable between 3000K, 4000K & 5700K

Wattage Switchable


IP66 for external use

Guarantee

Warranty	7 years
Battery Warranty	5 years
On-Site Warranty	2 years

Features & benefits

- Unique full length mounting slider allows complete freedom of mounting positions
- Quick connect through-wired version for side entry to avoid opening the product
- Versabox plug and play microwave sensor kit to automate lights off when no presence is detected
- Rear and side housing conduit entry points
- All installation points are marked on the outside of the luminaire to aid accurate pre-drilling, BESA mount accessory (ACBESA) sold separately
- Supplied with mounting clips, hanging bracket and compression glands at either end of luminaire
- ACKITMWS must be assembled by Collingwood Production only.



1200mm	
1500mm	92.3mm
1800mm	73mm